


Heptoda

6BE6


Oscylator i mieszacz

Miniaturowy



$$U_z = 6,3 \text{ V}$$

$$I_z = 0,3 \text{ A}$$



Wartości robocze

| | | | |
|-------------|----------------|----------------|------------|
| U_a | 100 | 250 | V |
| $U_{s2,4}$ | 100 | 100 | V |
| U_{s3} | -1,5 ... -30 | -1,5 ... -30 | V |
| U_{s1osc} | 10 | 10 | V |
| R_{s1} | 20 | 20 | k Ω |
| I_a | 2,8 | 3 | mA |
| $I_{a2,4}$ | 7,3 | 7,1 | mA |
| I_{s1} | 0,5 | 0,5 | mA |
| I_k | 10,1 | 10,2 | mA |
| S_p | 0,455 ... 0,01 | 0,475 ... 0,01 | mA/V |
| ρ_a | 0,5 | 1 | M Ω |

Wartości maksymalne

| | | |
|-------------------|-----|----|
| U_{amax} | 300 | V |
| U_{s1min} | -50 | V |
| U_{s1max} | 0 | V |
| $U_{s2,4}$ | 100 | V |
| I_{kmax} | 14 | mA |
| $P_{a\dot{a}max}$ | 1 | W |
| U_{wlkmax} | 90 | V |
| $P_{s2,4max}$ | 1 | W |
| $+U_{s3}$ | 0 | V |
| $-U_{s3}$ | -50 | V |

Pojemności

| | Bez ekranu | Z ekranem | |
|------------------|------------|-----------|----|
| $C_{s3/kmax}$ | ~ 7 | 7 | pF |
| $C_{a/k}$ | 8 | 13 | pF |
| $C_{s1/k} \leq$ | 5,5 | 5,5 | pF |
| $C_{s3/a} \leq$ | 0,3 | 0,25 | pF |
| $C_{s3/s1} \leq$ | 0,15 | 0,15 | pF |
| $C_{s1/a}$ | 0,05 | 0,05 | pF |
| $C_{s1/ks3}$ | 3 | 3 | pF |

TYPY PODOBNE

EK 90

