

TOSHIBA Fast Recovery Diode Silicon Diffused Type


## TFR2N, TFR2T

### Strobo Flasher Applications (Fast Recovery)

- Average forward current:  $I_F(AV) = 0.5 \text{ A}$
- Repetitive peak reverse voltage:  $V_{RRM} = 1000, 1500 \text{ V}$
- Reverse-Recovery Time:  $t_{rr} = 4 \mu\text{s}$

### Maximum Ratings ( $T_a = 25^\circ\text{C}$ )

Characteristics	Symbol	Rating	Unit
Repetitive peak reverse voltage	TFR2N	1000	V
	TFR2T	1500	
Average forward current	$I_{F(AV)}$	0.5	A
$I^2t$ limit value ( $t = 1\sim 10 \text{ ms}$ )	$I^2t$	2	$\text{A}^2\text{s}$
Peak one cycle surge forward current (non-repetitive)	$I_{FSM}$	20	A
Junction temperature	$T_j$	$-40\sim 125$	$^\circ\text{C}$
Storage temperature range	$T_{stg}$	$-40\sim 125$	$^\circ\text{C}$




Weight: 0.3 g (typ.)






### Electrical Characteristics ( $T_a = 25^\circ\text{C}$ )

Characteristics	Symbol	Test Condition	Min	Max	Unit
Peak forward voltage	$V_{FM}$	$I_{FM} = 0.5 \text{ A}$	—	1.5	V
Repetitive peak reverse current	$I_{RRM}$	$V_{RRM} = \text{Rated}$	—	10	$\mu\text{A}$
Reverse recovery time	$t_{rr}$	$I_F = 20 \text{ mA}, I_R = 1 \text{ mA}$	—	4	$\mu\text{s}$

### Marking



Code	Type
FR2N	TFR2N
FR2T	TFR2T



**RESTRICTIONS ON PRODUCT USE**

000707EAA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.  
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.