


# Pentoda mocy niezawodna

# 6516

Brimar


Wzmacniacz mocy m.cz.

Heptal



$$U_z = 6,3 \text{ V}$$

$$I_z = 0,2 \text{ A}$$



## Wartości charakterystyczne i robocze

$U_a$	250	V
$U_{s2}$	250	V
$U_{s1}$	-14	V
$U_{s3}$	0	V
$R_k$	740	$\Omega$

## Wartości graniczne

$U_{a0max}$	250	V
$P_{amax}$	4,0	W
$U_{s20max}$	250	V
$P_{s2max}$	0,60	W
$U_{wkmax}$	150	V

	min	śr.	max	
$I_{a0}$	12	15	18	mA
$I_{s20}$	1,3	2,0	2,7	mA
$S_a$	1,9	2,5	3,1	mA/V
$\varrho_a$		0,2		M $\Omega$
$K_{s1,s2}$		12		V/V
$R_a$		16		k $\Omega$
$U_{wej}$		5,3		V
$P_{wyj}$		1,4		W
$h$		10		%

## Pojemności

$C_{wej}$	4,25	pF
$C_{samax}$	0,3	pF
$C_{wyj}$	6,5	pF

U w a g a. Nóżka 6 ma wewnętrzne połączenia

TYPY PODOBNE

**CV 4063, EL 91**

