

Pentoda (tetroda) strumieniowa

**6 L 50**


Tesla

Wzmacniacz mocy m.cz. i obrazowy

Nowal

6L50

$U_z = 6.3V$   
 $I_z = 1A$



**Wartości robocze**

$U_a$	200	200	V
$U_{s2}$	250	250	V
$U_{s3}$	0	0	V
$U_{s1}$	-12,5	-50	V
$I_a$	70	1	mA
$I_{s2}$	6	—	mA
$S_a$	5	—	mA/V
$\varrho_a$	16	—	k $\Omega$
$R_a$	2,5	—	k $\Omega$
$R_k$	180	—	$\Omega$

**Wartości maksymalne**

$U_{amax}$	1000	V
$U_{s2max}$	400	V
$P_{amax}$	25	W
$P_{s2max}$	3,5	W
$R_{s1max}$	1	M $\Omega$
$I_{kmax}$	125	mA
$U_{wlkmax}$	50	V

**Pojemności**

$C_{s1/a}$	< 0,3	pF
------------	-------	----

TYPY PODOBNE

6 BG 6 G, 6 L 6, EL 38