

Pentoda mocy

VL1


Wzmacniacz mocy m.cz.

Bocznostykowy



$$U_z = 55V$$

$$I_z = 50mA$$



Wartości charakterystyczne i robocze

U_a	100	200	V
U_{s2}	100	200	V
U_{s1}	-5,5	-14	V
R_k	370	500	Ω
I_a	13	25	mA
I_{s2}	1,9	3,5	mA
S_a	2	2,2	mA/V
R_a	8	8	k Ω
ρ_a	50	50	k Ω
P_a	0,3	1,6	W
U_{wej}	3,6	10	V
$U_{wej}^1)$	1,25	2,8	V
h	—	10	%

¹⁾ $P_{wyj} = 50 \text{ mW}$

Wartości graniczne

U_{amax}	250	V
U_{s2max}	250	V
P_{amax}	5	W
P_{s20max}	1	W
R_{s1max}	0,7	M Ω
R_{wlkmax}	5	k Ω
U_{wlkmax}	175	V

Pojemność

$C_{s1/amax}$	1	pF
---------------	---	----

TYPY PODOBNE

CL 1

