LM6152 Dual and LM6154 Quad High Speed/Low Power 45 MHz Rail-to-Rail I/O Operational Amplifiers

General Description

Using patent pending circuit topologies, the LM6152/54 provides new levels of speed vs power performance in applications where low voltage supplies or power limitations made compromise necessary. With only 1.5 mA/amp supply current, the 45 MHz bandwidth of this device supports new portable applications where higher power devices unacceptably drain battery life.

In addition, the LM6152/54 can be driven by voltages that exceed both power supply rails, thus eliminating concerns over exceeding the common-mode voltage range. The rail-to-rail output swing capability provides the maximum possible dynamic range at the output. This is particularly important when operating on low supply voltages. The LM6152/54 can also drive capacitive loads without oscillating.

Operating on supplies of 1.8V to over 24V, the LM6152/54 is excellent for a very wide range of applications, from battery operated systems with large bandwidth requirements to high speed instrumentation.

Features (For 5V Supply)

- Rail-to-rail input CMVR -0.25V to 5.25V (max/min)
- Rail-to-rail output swing
- 0.01V to 4.99V (max/min) 45 MHz (typ) @ 50 kHz
- Wide gain-bandwidth: ■ Slew rate
- 30 V/μs (typ)
- Low supply currentWide supply range


1.5/Amp (typ) 1.8V to 24V

- Fast settling time:
- Gain ■ PSRR
- 108 dB (typ) with $R_L = 10k$ 87 dB (typ)


Applications

- Portable high speed instrumentation
- 5V signal conditioning amplifiers/ADC buffers
- Bar code scanners
- Wireless communications

Connection Diagrams



Top View



Top View

Ordering Information

Package	Temperature Range Industrial - 40°C to +85°C	NSC Drawing
8-Pin Small Outline	LM6142AIM, LM6142BIM	M08A
14-Pin Molded DIP	LM6144AIN, LM6144BIN	N14A
14-Pin Small Outline	LM6144AIM, LM6144BIM	M14A

TL/H/12350-1