





T.			$U_f$	$I_f$	$U_a$	$I_a$	$S$	$\mu$	$R_i$	$R_k$	$P_a$
			V	A	V	mA	mA/V	V/V	k $\Omega$	$\Omega$	W
<b>6 C 7 B</b>	CCCP	2	6,3	0,2	$\left\{ \begin{array}{l} 250 \\ 300 \end{array} \right.$	4,5	4	66	16,5	400	1,3
<b>5744</b>	amer	2	6,3	0,2		250	4	4	70	17,5	
<b>6247<sup>1)</sup></b>	Ray	1	6,3	0,2	250	4,2	2,65	60	23	500	

<sup>1)</sup> vide \*4    <sup>2)</sup> vide \*4, a, b, c, d, e, f, g

#### Equivalents

<b>CK 619 CX</b>	Ray = 5744	<b>CK 6247</b>	Ray = 6247	<b>6151</b>	amer = 5744
<b>CK 5744</b>	Ray = 5744	<b>6 C 2 B</b>	CCCP = 6 C 7 B	<b>6190</b>	amer = 5744
<b>CK 5744 WA<sup>2)</sup></b>	Ray = 5744	<b>5744 WA<sup>2)</sup></b>	amer = 5744		



T.	$C_{a/g}$	$C_{g/k}$	$C_{a/k}$	$C_{f k}$	vide
	pF	pF	pF	pF	
6 C 7 Б	1	3,3	3,4	3,8	*6
5744	0,83	2,6	0,9		*5
6151	0,85	2,6	0,8		*5

