## PATRIOT GUITAR SERIES

# THE COPPERHEAD<sup>™</sup>

The Eminence Copperhead guitar speaker combines the best of two tones, balancing country honk with a touch of classic blues. Extremely balanced vintage tone for smooth, driven leads and clean rhythm.



**10**<sup>"75</sup> WATTS 8 Ω


SPECIFICATION

#### MOUNTING INFORMATION

### MATERIALS OF CONSTRUCTION

Nominal Basket Diameter	10", 254 mm	Enclosure Type		Copper voice coil
Nominal Impedance*	8 Ω	Closed Back	Acceptable	Polyimide former
Power Rating*	75 W	Open Back	Acceptable	Ferrite magnet
Resonance (Fs)	105 Hz	Driver Volume Displaced	0.034 cu.ft., 0.95 liters	Non-vented core
Usable Frequency Range	80 Hz – 4.5 kHz	Overall Diameter	10.11", 256.8 mm	Pressed steel basket
Sensitivity*	98.8 dB	Baffle Hole Diameter	9.13″, 231.9 mm	Paper cone
DC Resistance (Re)	7.59 Ω	Depth	4.2", 106.7 mm	Paper cone edge
Qts	0.98	Front Sealing Gasket	Yes	Zurette dust cap
Magnet Weight	20 oz.	Rear Sealing Gasket	Yes	
Gap Height	0.31″, 7.9 mm	Mounting Holes Diameter	0.23", 5.8 mm	
Voice Coil Diameter	1.5″, 38 mm	Mounting Holes B.C.D.	9.6″, 243.8 mm	
		Net Weight	4.5 lbs , 2.04 kg	
		Shipping Weight	6.4 lbs , 2.9 kg	

#### FREQUENCY RESPONSE & IMPEDANCE CURVE\*







See footnotes on page 155 for information regarding usable frequency range, nominal impedance, power rating and sensitivity.