

IMI

Tuning Indicator Ball and Line Display 1.4V, 25mA Filament

Typical Operation (Battery)

	Pin 5 earthed	Pin 4 earthed	
V_a	60	90	V
V_g	0	0	V
I_a	120	250	μA
V_g for cut-off	-8	-13.5	V

Typical Operation (Mains)

	earth pin 5	
$V_{a(b)}$	110	V
V_g	0	V
I_a	90	μA
R_a	560	k Ω
V_g for cut-off	-15	V

B8D

