

6C12

HF Triode Heptode Frequency Changer 6.3V, 0.3A Heater

Typical Operation

	Triode	Heptode	
$V_{a(b)}$	250	250	V
V_{g2}	...	103	V
V_{g1}	...	-2	V
I_a	4.5	3.25	mA
I_{g2}	...	6.7	mA
R_a	33	...	k Ω
R_{gt+g3}	...	47	k Ω
R_{g2+g4}	...	22	k Ω
R_k	140	...	Ω
g_c	...	0.775	mA/V

B9A

