

# DK92

## Pentagrid Frequency Changer 1.4V, 50mA Filament

### Typical Operation

$V_a$	85	V
$V_{g4}$	60	V
$V_{g3}$	0	V
$V_{g2(osc)}$	30	V
$I_a$	0.7	mA
$I_{g2(osc)}$	1.6	mA
$I_{g4}$	150	$\mu A$
$R_{g4}$	180	k $\Omega$
$R_{g2(osc)}$	33	k $\Omega$
$R_{g1(osc)}$	27	k $\Omega$
$g_c$	325	$\mu A/V$
$r_a$	650	k $\Omega$

