

Wskaźnik dostrojenia


EM 5

Bocznostykowy

EM5

$$U_{\dot{z}} = 6,3 \text{ V}$$

$$I_{\dot{z}} = 200 \text{ mA}$$



Wartości robocze

U_{ab}	250	V
U_{s2}	0... -4	V
	0... -20	
I_a	0,1 0,2	mA
I_L	0,46	mA
β	75... 15°	
β	83... 5°	

Wartości graniczne

U_{amax}	300	V
P_{amax}	po 0,5	W
I_{kmax}	5	mA
R_{gmax}	3	MΩ
U_{Lmax}	250	V
U_{Lmin}	90	V

TYPY PODOBNE

EM 4, EM 11