



T.			U_f	I_f	Cl.	f	U_a	U_g	I_a	I_g	S	μ	R_i	P_{dr}	P_o	P_a
			V	A		MHz	V	V	mA	mA	mA/V	V/V	k Ω	W	W	W
OQ 10/400	Tu	1	4	1,1	C-Tgr	15	500	- 50	30	7,5	(A-Mod)	25	11	0,83	15	10
					C-Tlf	500	- 50	33,5	6	0,8				10		
					stat	60	600	maximum	2,3							
OQ 15/600	Tu	2	4	1	C-Tgr	10	600	- 75	80	11	(A-Mod)	8	2	1,5	35	15
					C-Tlf	490	- 60	45	6	0,7				15		
					C-Tlf	600	- 75	38	0	0,5				7,5		
					stat	120	600	maximum	4							
TY 04-30	Mul	3	2	3,65	C-Tgr	30	400	-120	130	24	(G-Mod)	6,5	3,25	5,8	23	30
					C-Tlf	400	-150	125	24	6,7				23		
					B-Tlf	400	- 55	97	33	7,5						
					stat	100	450	maximum	2							

T.	C_g	C_o	$C_{g/a}$
	pF	pF	pF
OQ 10/400	3,5	3	6,8
OQ 15/600	4,5	7	9
TC 04/10	3,5	3	5,5
TY 04-30	1,2	0,8	1,9

Equivalents

E 140	SFR = OQ 10/400
OP 10/400	Tu = OQ 10/400
TC 04/10	Phi = OQ 10/400
TZ 04-10	Mul = OQ 10/400
3316 A	LMT = TY 04-30

